Mini-slide SLTE, electric Motor controller SFC-DC

FESTO



Precise, simple and powerful

Absolute precision guaranteed: Mini-slide SLTE, electric



Positioning – precise, reliable and extremely compact, with integrated controller.

The electrical mini-slide SLTE allows slow or fast, gentle or dynamic motion. It is freely positionable and has a precision, resilient guide. Its design platform: the tried-and-tested SLT supplemented with low-noise lead screw spindle. Motors with an integrated encoder are available as the drive. For working loads up to max. 4 kg and fast positioning times (50 mm in approx. 400 ms).

Simply impressive

Thanks to IP54, the external controller SFC-DC can be flexibly mounted either in the field or in a control cabinet.

Simple system planning

Based on the design platform of the SLT, the SLTE is equipped with identical interfaces and is fully compatible with the modular handling and assembly system and SLT adapter kits.

Simple selection and commissioning

The SLTE concept includes installation options for supply lines as well as:

 Easy input of positioning records at the controller via the man-machine interface or via the computer-aided Festo configuration tool.



Mini-slide SLTE and motor controller SFC-DC: precise, simple and powerful.

- 1 The mechanical interfaces are identical to the pneumatic minislide SLT and compatible with Festo's modular handling system. This allows pick & place units or 2D/3D gantries to be implemented quickly and reliably.
- 2 Precise and resilient: the triedand-tested ball bearing guide of the SLTE. It ensures good rigidity and high positioning accuracy even with high loads and dynamic motion.
- 3 Just one cable is used to electrically connect the SLTE to the motor controller SFC-DC with integrated power electronics.

 Thanks to IP54, the SFC-DC can be mounted in the field at a userfriendly location next to the drive.
- 4 The integrated DC motor and the low-noise lead screw spindle with integrated gear unit ensure fast positioning times at working loads up to 4 kg.

Key features

FESTO

Range of applications


The electric mini slide SLTE is ideal for use in automation applications where controlled end-position cushioning (gentle stopping), constant travel speed and positioning capability are important factors.

The SLTE has the same interfaces on the yoke, slide and underneath the housing as the pneumatic SLT. It is also fully compatible with the modular handling and assembly system and SLT adapter kits.

Special features

- Precise and rigid guide
- Freely positionable
- Fast positioning times
- Through-holes from above and below
- Sensors can be integrated
- Gentle starting and stopping
- Working loads up to 4 kg
- Constant travel speeds of 2 ... 200 mm/s

Everything from a single source



The mini slide SLTE and motor controller SFC form one unit.

- Thanks to the protection class IP54, the SFC can be mounted close to the SLTE, either:
 - with centre supports
- on an H-rail
- Only one cable required between SLTE and SFC
- Motor controller SFC available with or without control panel
- Easy control with
 - I/O interface
 - Profibus
 - CANopen
- DeviceNet

Parameterisation possible via


- Control panel:
 - Suitable for simple position sequences
- Configuration package FCT (Festo configuration tool):
 - Parameterisation via RS 232 interface
 - Windows-based PC user interface (Festo configuration tool)







The technology in detail



- 1 Drive rod
- 2 Slot for reference switch
- 3 Roller bearing guide
- 4 Drive assembly consisting of DC motor with displacement encoder
- 5 Electrical connection
- 6 Threaded holes and throughholes with centring hole for attaching the working load
- 7 Threaded holes and throughholes with centring hole for attaching the SLTE
- 8 Fixed stop with integrated rubber buffer

Mini slides SLTE, electric Key features






Comparison between electric mini slide SLTE and pneumatic mini slide SLT

Advantages	Electrical: SLTE	Pneumatic: SLT
Advantages	Gentle starting and stopping	High feed force
	 Constant and precise speed (2 200 mm/s) Flexible positioning without mechanical devices Programmable drive profile 	 High speed Fast positioning time Compact length
Guide		
 Preloaded, backlash-free, precise and rigid ball bearing cage guide High torque and load absorption 	Guide rail for slide Ball bearing Guide rail on drive body	
Dimensions		
Identical width and height dimensions Type Width (W) x Height (H) SLT(E)-10 50 x 30 mm SLT(E)-16 66 x 40 mm		
Interfaces		
Identical mounting and attachment options Attachment surfaces: Direct mounting using threaded holes and through-holes Mounting surfaces: Direct mounting of loads and devices (e.g. SLT: semi-rotary drives and grippers) via threaded holes in the slide and the yoke plate	2	1 2
Technical data		
Piston ∅ [mm]	10, 16	6 25
Stroke [mm]	50 150	10 200
Max. speed [m/s]	0.2	0.8
Repetition accuracy at end positions [mm]	±0.1	±0.02
Intermediate positions	Any	None


System product for handling and assembly technology



Syste	em elements and accessories		
		Brief description	→ Page/Internet
1	Axes	Wide range of combinations possible within handling and assembly technology	axes
2	Grippers	Wide range of variations possible within handling and assembly technology	gripper
3	Adapters	For drive/drive and drive/gripper combinations	adapter kit
4	Basic mounting components	Profiles and profile connectors as well as profile/drive connectors	basic component
5	Installation components	For manageable and secure guidance of electrical cables and tubing	installation component
-	Drive units	Wide range of combinations possible within handling and assembly technology	drive

Mini slides SLTE, electric Peripherals overview






Acces	Accessories					
		Brief description	→ Page			
1	Mini slide	Electromechanical linear axis with lead screw spindle	9			
	SLTE					
2	Centring pin/sleeve	 For centring loads and attachment components 	17			
	ZBS/ZBH	 Centring sleeves included in scope of delivery 				
3	Proximity sensor	For referencing mini slide or for sensing slide position	17			
	SME/SMT-10					
4	Motor cable	Connecting cable between motor and motor controller	18			
	KMTR					
5	Motor controller	For parameterising and positioning mini slide	18			
	SFC					
6	Control cable	For I/O connection to any controller	18			
	KES					
6	Plug	For fieldbus interface	18			
	FBS, FBA					
7	Buffer	Buffer included in scope of delivery	-			
8	Supply cable	Power supply cable; load and logic power supplies are isolated	18			
	KPWR					
9	Centre supports	- For mounting motor controller	18			
	MUP	- Motor controller can also be mounted on H-rail				



Type codes


8



Mini slides SLTE, electric Technical data



Function









General techni	eneral technical data				
Size			10	16	
Constructional	design		Electromechanical linear axis with lead screw		
Guide			With ball bearings		
Type of mountir	ng		Via through-holes		
			Via female thread		
			Via female thread and centring sleeve		
Stroke		[mm]	50,80	50, 80, 100, 150	
Stroke reserve per end	with rubber buffer at both ends	[mm]	0.5	0.6	
position	with rubber buffer at one end	[mm]	1.2	1.25	
Assembly posit	ion		Any		
Lead screw pitc	h	[mm]	5	7.5	
Min. travel speed [mm/s]		[mm/s]	2		
Max. acceleration	Max. acceleration [m/s ²]		2.5		
Repetition accuracy [mm]		[mm]	±0.1		
Reversing back	lash	[mm]	< 0.1		

Electrical data for motor					
Size		10	16		
System resolution of encoder		512 (pulses per rotation)	1,000 (pulses per rotation)		
Nominal operating voltage	[V DC]	24			
Output	[W]	4.5	18		

Operating and environmental conditi	Operating and environmental conditions					
Size		10	16			
Ambient temperature	[°C]	0 +40				
Protection class		IP40				
Fast transients		To EN61000-4-4				
Max. noise level ¹⁾	[dB A]	< 50	< 55			
CE symbol (declaration of conformity)		In accordance with EU EMC directive				

¹⁾ At maximum permissible speed

Weight [g]							
Size	10		16				
Stroke	50	80	50	80	100	150	
Product weight	574	737	1,185	1,465	1,714	2,196	
Moving load	163	235	296	415	519	729	



4




Materials Sectional view 1 3 2


Mini slide	
1 Lead screw	High-alloy steel
2 Motor housing	Wrought aluminium alloy, anodised
3 Housing	Wrought aluminium alloy, anodised
4 Slide	Wrought aluminium alloy, anodised
5 Guide	Tempered steel
– Seals	Thermoplastic rubber, nitrile rubber

5

Travel speed v as a function of applied load m


Horizontal mounting position






Vertical mounting position SLTE-10







SLTE-16



Technical data



Positioning time t as a function of stroke l SLTE-10 SLTE-16 2000 ₹3000 1750 2500 1500 1250 2000 1000 1500 750 1000 500 500 250 0 0 10 20 30 40 50 60 70 n 120 l [mm] l [mm] - v = 50 mm/s ---- v = 125 mm/s • v = 50 mm/s -- v = 125 mm/s ----- v = 65 mm/s ••••• v = 65 mm/s ---- v = 150 mm/s ---- v = 150 mm/s --- v = 80 mm/s -- v = 80 mm/s **---** v = 170 mm/s **-** - v = 170 mm/s •••• v = 210 mm/s

Reference travel

to fixed stop

Positive fixed stop

•••••• v = 100 mm/s

- To front stop bush (extended)


Negative fixed stop


- To rear stop bush (retracted)

to proximity sensor

Position freely selectable

•••••• v = 100 mm/s







The following applies for reference travel to a fixed stop:

Positive fixed stop

Negative fixed stop





Size	Stroke	L11			
		Positive fixed stop	Negative fixed stop		
10	50	67.4 ^{+1.1}	15.6 _{-1.1}		
	80	97.0 ^{+1.1}	15.2 _{-1.1}		
16	50	74.9 ^{+1.1}	23.1 _{-1.1}		
	80	104.1+1.1	22.3 _{-1.1}		
	100	124.6+1.1	22.8-1.1		
	150	173.3 ^{+1.1}	21.5 _{-1.1}		


Technical data

FESTO

Dynamic characteristic load values

Torques are indicated with reference to the centre of the guide.


They must not be exceeded in the dynamic range. Special attention must be paid to the cushioning phase.




If the drive is subjected to more than two of the indicated forces and torques simultaneously, the following equation must be satisfied in addition to the indicated maximum loads:

$$\frac{|Fy|}{Fy_{max.}} + \frac{|F_Z|}{Fz_{max.}} + \frac{|Mx|}{Mx_{max.}} + \frac{|My|}{My_{max.}} + \frac{|Mz|}{Mz_{max.}} \leq 1$$

Position of the guide centre





+ plus stroke length

Permissible forces and torques G						Geometric characteristics	
Size	Stroke	Fy _{max}	Fz _{max}	Mx _{max} , My _{max}	Mz _{max}	H13	L21
		[N]	[N]	[Nm]	[Nm]	[mm]	[mm]
10							
	50	390	390	3.1	1.4	13	33.5
	80	410	410	4.3	1.5		41
16							
	50	510	510	4.6	2.8	16	35
	80	520	520	6.0	2.8		41.5
	100	600	600	9.1	3.2		51.5
	150	660	960	12.6	3.5		66.5




Engineering Tool
PositioningDrives
www.festo.com/en/engineering

Technical data



Calculation example

Given:





 $\begin{array}{lll} \mbox{Mini slide} & = \mbox{SLTE-10} \\ \mbox{Stroke length} & = \mbox{80 mm} \\ \mbox{Lever arm } \mbox{Lever arm } \mbox{Ly} & = \mbox{50 mm} \\ \mbox{Lever arm } \mbox{Ly} & = \mbox{30 mm} \\ \mbox{Weight } \mbox{F}_{z} & = \mbox{0.8 kg} \\ \mbox{Acceleration a} & = \mbox{0 m/s}^{2} \end{array}$

To be found:

F_y, F_z, Mx, My, Mz
and verification of function with
combined load

Solution:

L21 = 41 mm from table

$$F_y = 0 N$$

$$F_z = m x g$$

= 0.8 kg x 9.81 m/s² = 7.848 N

$$M_X = m \times g \times L_y$$

= 0.8 kg x 9.81 m/s² x 30 mm = 0.236 Nm

$$M_y = m \times g \times [(L21+stroke)-L_x]$$

= 0.8 kg x 9.81 m/s² [(41 mm + 80 mm) - 50 mm] = 0.557 Nm


 $M_Z = 0 Nm$

Combined load:

$$\frac{|Fy|}{Fy_{max.}} + \frac{|Fz|}{Fz_{max.}} + \frac{|Mx|}{Mx_{max.}} + \frac{|My|}{My_{max.}} + \frac{|Mz|}{Mz_{max.}}$$


$$= 0 + \frac{7.848N}{410N} + \frac{0.2366Nm}{4.3Nm} + \frac{0.557Nm}{1.5Nm} + 0 = 0.445 \le 1$$

Pin allocation of connection plug



Plug I	Plug M12				
Pin	Connection	Function			
1	Motor +	Motor conductor			
2	Motor –	Motor conductor			
3	A	Encoder signal RS 485			
4	A/	Encoder signal RS 485			
5	В	Encoder signal RS 485			
6	B/	Encoder signal RS 485			
7	I	Encoder signal RS 485			
8	1/	Encoder signal RS 485			
9	+5 V DC	Signal supply			
10	0 V	Signal ground			
11	-	-			
12	-	-			

Technical data





¹⁾ End position at fixed stop


End position at rubber buffer

Mini slides SLTE, electric Technical data









Mini slides SLTE, electric Technical data



Ordering data			
Size	Brief description	Part No.	Туре
10			
	Mini slide	537 447	SLTE-10-50-LS-G04
		537 449	SLTE-10-80-LS-G04
16			
	Mini slide	537 459	SLTE-16-50-LS-G04
		537 461	SLTE-16-80-LS-G04
		537 463	SLTE-16-100-LS-G04
		537 465	SLTE-16-150-LS-G04
0)			

Mini slides SLTE, electric Accessories





Ordering data	Ordering data - Centring sleeves¹) Technical data → Internet: zb					
Size		10		16		
		Part No.	Туре	Part No.	Туре	
(1)	Housing	186 717	ZBH-7	150 927	ZBH-9	
	Slide	189 652	ZBH-5	189 652	ZBH-5	

1) Scope of delivery: 10 per pack

Ordering data	– Proximity sensors for C-sl		Technical data → Internet: sm			
	Type of mounting	Switch output	Electrical connection, connection direction	Cable length [m]	Part No.	Туре
N/O contact						
	Insertable in the slot from	PNP	Cable, 3-wire, in-line	2.5	525 915	SMT-10F-PS-24V-K2,5L-OE
	above, flush with cylinder		Plug M8x1, 3-pin, in-line	0.3	525 916	SMT-10F-PS-24V-K0,3L-M8D
	profile		Plug M8x1, 3-pin, lateral	0.3	526 675	SMT-10F-PS-24V-K0,3Q-M8D
	Insertable in the slot	PNP	Plug M8x1, 3-pin, in-line	0.3	173 220	SMT-10-PS-SL-LED-24
	lengthwise		Cable, 3-wire, in-line	2.5	173 218	SMT-10-PS-KL-LED-24

Ordering data	- Proximity sensors for C-sl		Technical data → Internet: sm			
	Type of mounting	Switch output	Electrical connection, connection direction	Cable length [m]	Part No.	Туре
N/O contact						
	Insertable in the slot from	Contacting	Plug M8x1, 3-pin, in-line	0.3	525 914	SME-10F-DS-24V-K0,3L-M8D
	above, flush with cylinder		Cable, 3-wire, in-line	2.5	525 913	SME-10F-DS-24V-K2,5L-OE
	profile		Cable, 2-wire, in-line	2.5	526 672	SME-10F-ZS-24V-K2,5L-OE
a	Insertable in the slot	Contacting	Plug M8x1, 3-pin, in-line	0.3	173 212	SME-10-SL-LED-24
	lengthwise		Cable, 3-wire, in-line	2.5	173 210	SME-10-KL-LED-24

Ordering data	- Connecting cables		Technical data → Internet: nebu		
	Electrical connection, left	Electrical connection, right	Cable length	Part No.	Туре
			[m]		
	Straight socket, M8x1, 3-pin	Cable, open end, 3-wire	2.5	541 333	NEBU-M8G3-K-2.5-LE3
OF THE PARTY OF TH			5	541 334	NEBU-M8G3-K-5-LE3
	Angled socket, M8x1, 3-pin	Cable, open end, 3-wire	2.5	541 338	NEBU-M8W3-K-2.5-LE3
			5	541 341	NEBU-M8W3-K-5-LE3

Key features

FESTO

Hardware

- The motor controller SFC-DC serves as a positioning controller and closed loop position controller
- Available with or without control panel
- Thanks to IP54 protection, the motor controller can be mounted close to the drive

Parameter assignment via:

- Control panel:
- suitable for simple position sequences
- FCT (Festo Configuration Tool) configuration package:
 - with RS 232 interface
 - Windows-based PC user interface, Festo Configuration Tool
- Easy actuation via:
 - I/O interface
- Profibus
- CANopen
- DeviceNet







For controlling

Mini slide SLTE



FHPP - Festo Handling and Positioning Profile

Optimised data profile

Festo has developed an optimised data profile, the "Festo Handling and Positioning Profile (FHPP)", that is tailored to the target applications for handling and positioning tasks.

The FHPP data profile permits the actuation of Festo motor controllers, using a fieldbus interface, via standardised control and status bytes.

The following are defined, among others:

- Operating modes
- I/O data structure
- Parameter objects
- Sequence control





• • •


Set selection Direct operation Parameter channel Free access to all parameters for reading and writing Parameters for reading and writing





FCT software - Festo Configuration Tool

Software platform for electrical drives from Festo




- All the drives in a system can be managed and archived in a common project
- Project and data management for all supported device types
- Simple to use thanks to graphically supported parameter entry
- Universal mode of operation for all drives
- Working offline at your desk or online at the machine

Mechanical reference positions and limit positions



- Reference positions can be either edited or taught in
- Flexible adaptation to installation conditions
- Settings are displayed clearly


Position set table



- 31 position sets ensure flexibility in positioning
- Absolute or relative positioning values can be used
- The following parameters can be set flexibly for each application:
 - Position
 - Speed
 - Acceleration
 - Braking ramps
- Complete function test



Type codes



Technical data

FESTO

Fieldbus interfaces









General technical data							
Туре		SFC10	SFCPB	SFCCO	SFCDN		
Operating mode		Cascade closed-loop contro	oller with	 PI closed-loop speed co 	ontroller		
		 P current regulator 		 P position regulator 			
Position sensor		Encoder					
Encoder input		RS485/RS422, A/B signal	with index pulse				
Display (optional)		Four-key interface with full	-text display via graphic LC	D display (128 x 64 pixels)			
Control elements (optional)		4 keys					
Interface		I/O interface for 31 posi-	Profibus DP	CANopen	DeviceNet		
		tion sets and homing					
Number of digital logic inputs		8	-	-	-		
Number of digital logic outputs		4		-	-		
Bus terminating resistor ¹⁾		-	- Not integrated in the device				
Communication profile		-	DP-V0/V1 / FHPP	DS301; / FHPP	FHPP		
		-	Step7 functional mod-	DS301; DSP402	Device Type 0C _h		
			ules				
Max. fieldbus baud rate	[Mbit/s]	-	12	1	0.5		
Type of mounting		H-rail, wall or surface bracket					
Product weight	[g]	600					

¹⁾ Details of bus terminating resistor → 25


Electrical data		
General		
Rated output	[W]	75
Parameterisation interface		RS232; 9600 baud
Load supply		
Nominal voltage	[V DC]	24 ±10%
Nominal current	[A]	3
Peak current	[A]	5
Logic cumply		
Logic supply		
Nominal voltage	[V DC]	24 ±10%
Nominal current	[A]	0.1
Peak current	[A]	0.8
Max. current per output	[A]	0.5
(digital logic outputs)		


Technical data




Operating and environmental conditions	perating and environmental conditions						
Туре	SFC10	SFCPB	SFCCO	SFCDN			
Digital logic outputs	Electrically isolated	-	-	-			
Logic inputs	Electrically isolated	-	-	-			
Specification, logic input	IEC 61131	-	-	-			
Protection class	IP54						
Vibration resistance	To DIN EN 60068-2-6						
Shock resistance	To DIN EN 60068-2-27	To DIN EN 60068-2-27					
Protective function	I ² t monitoring						
	Current monitoring						
	Voltage failure detectio	n					
	Lag error monitoring						
	Software end position detection						
CE mark (see declaration of conformity)	In accordance with EU EMC directive						
Ambient temperature [°C]	nt temperature [°C] 0 +40						
Storage temperature [°C]	-25 +60						
Relative air humidity [%]	0 95 (non-condensin	0 95 (non-condensing)					

Pin allocation







1 Re	1 Reference switch, 3-pin M8 socket				
Pin	Function				
1	24 V				
4	Reference input				
3	0 V				
-					

2 RS	2 RS 232 interface, 4-pin M8 socket		
Pin	Function		
1	0 V		
2	Transmitted Data (TxD)		
3	Received Data (RxD)		
4	-		

DeviceNet interface

Technical data



3 I/O	interface, 15-pin Sub-D plug
Pin	Function
1	24 V (supply for output)
2	Position set coding, bit 1
3	Position set coding, bit 2
4	Position set coding, bit 3
5	Position set coding, bit 4
6	Position set coding, bit 5
7	Stop bit
8	0 V
9	Enable bit
10	Start bit
11	MC
12	Ready
13	Acknowledge
14	Error
15	0 V

3 Pro	3 Profibus interface, 9-pin Sub-D socket				
Pin	Function				
1	-				
2	-				
3	RxD/TxD-P				
4	CNTR-P				
5	DGND				
6	VP				
7	-				
8	RxD/TxD-N				
9	1				

3 CAI	3 CANopen interface, 9-pin Sub-D plug				
Pin	Function				
1	-				
2	CAN_L				
3	CAN_GND				
4	_				
5	CAN_SHLD				
6	CAN_V-				
7	CAN_H				
8	_				
9	CAN_V+				

3 De	3 DeviceNet interface, 9-pin Sub-D plug			
Pin	Function			
1	-			
2	CAN_L			
3	CAN_GND			
4	-			
5	CAN_SHLD			
6	CAN_V-			
7	CAN_H			
8	-			
9	CAN_V+			


4 Mo	4 Motor interface, 15-pin Sub-D socket					
Pin	Function					
1	VCC logic					
2	Encoder channel A					
3	Encoder channel A/					
4	Encoder channel B					
5	Encoder channel B/					
6	Encoder channel C					
7	Encoder channel C/					
8	Logic 0 V					
9	0 V					
10	0 V					
11	0 V					
12	Motor +					
13	Motor-					
14	0 V					
15	0 V					

5 Pov	Power supply, 7-pin plug				
Pin	Function				
A1	24 V (load)				
A2	0 V (load)				
1	24 V (logic)				
2	0 V (logic)				
3	1				
4	PE				
5	1				



FESTO

Technical data



Ordering data			
	Brief description	Part No.	Туре
	Motor controller with I/O interface		
	Without control panel	538 912	SFC-DC-VC-3-E-H0-IO
	With control panel	538 913	SFC-DC-VC-3-E-H2-IO
	Motor controller with Profibus interface		
	Without control panel	540 366	SFC-DC-VC-3-E-H0-PB
	With control panel	540 367	SFC-DC-VC-3-E-H2-PB
	Motor controller with CANopen interface		
	Without control panel	540 364	SFC-DC-VC-3-E-H0-CO
	With control panel	540 365	SFC-DC-VC-3-E-H2-CO
	Motor controller with DeviceNet interface		
	Without control panel	540 368	SFC-DC-VC-5-E-HO-DN
	With control panel	540 369	SFC-DC-VC-5-E-H2-DN





Ordering data – Cables					
	Brief description	Cable length [m]	Part No.	Туре	
	Supply cable,	2.5	538 914	KPWR-MC-1-SUB-15HC-2,5	
	for connecting load and logic supply	5	538 915	KPWR-MC-1-SUB-15HC-5	
		10	538 916	KPWR-MC-1-SUB-15HC-10	
	Motor cable,	2.5	538 917	KMTR-DC-SUB-15-M12-2,5	
200 J	for connecting motor and controller	5	538 918	KMTR-DC-SUB-15-M12-5	
		10	539 316	KMTR-DC-SUB-15-M12-10	
	Control cable,	2.5	538 919	KES-MC-1-SUB-15-2,5	
	for I/O interface to any controller	5	538 920	KES-MC-1-SUB-15-5	
		10	538 921	KES-MC-1-SUB-15-10	
	Programming cable, for parameterisation and commissioning via RS232 interface using FCT software	2.5	537 926	KDI-MC-M8-SUB-9-2,5	

Ordering data - Plugs				
	Brief description	Part No.	Туре	
Plug for Profibus				
	 9-pin Sub-D connection Bus terminating resistor integrated Position of DIL switch can be read externally IP65 	532 216	FBS-SUB-9-GS-DP-B	
Bus connection adapte	r for Profibue			
Dus connection adapte	9-pin Sub-D plug to 5-pin round plug/socket M12 Bus terminating resistor must be connected externally	533 118	FBA-2-M12-5POL-RK	
Plug for CANopen and I	I Devise Not	ı		
	 9-pin Sub-D connection Bus terminating resistor integrated Position of DIL switch can be read externally IP65 	532 219	FBS-SUB-9-BU-2x5POL-B	
Due connection adapte	r for CANopen and DeviceNet			
Bus connection adapte	- 9-pin Sub-D plug to 5-pin round plug/socket M12 - Bus terminating resistor must be connected externally	525 632	FBA-2-M12-5POL	
Sund S	 9-pin Sub-D plug on 5-pin strip Bus terminating resistor must be connected externally 	525 634	FBA-1-SL-5POL	
	 5-pin terminal strip for connecting the fieldbus cable to the bus connection adapter FBA-1-SL-5POL 	525 635	FBSD-KL-2x5PIN	



Accessories

Ordering data – Central supports					
	Brief description	Part No.	Туре		
	Centre supports for mounting controller	160 909	MUP-8/12		

Ordering data – Software					
	Brief description	Part No.	Туре		
	Operating package contains: - CD-ROM - with user documentation for SFC-DC, in the languages de, en, es, fr, it, sv - with configuration software FCT (Festo Configuration Tool) - Brief description This operating package is included in the scope of delivery.	550 140	P.BP-SFC-DC		

Ordering data - Docu	mentation ¹⁾		
	Language	Part No. Type	Part No. Type
		For I/O interface	For Profibus interface
	DE	540 417 P.BE-SFC-DC-IO-DE	540 411 P.BE-SFC-DC-PB-DE
	EN	540 418 P.BE-SFC-DC-IO-EN	540 412 P.BE-SFC-DC-PB-EN
	ES	540 419 P.BE-SFC-DC-IO-ES	540 413 P.BE-SFC-DC-PB-ES
	FR	540 420 P.BE-SFC-DC-IO-FR	540 414 P.BE-SFC-DC-PB-FR
	IT	540 421 P.BE-SFC-DC-IO-IT	540 415 P.BE-SFC-DC-PB-IT
	SV	540 422 P.BE-SFC-DC-IO-SV	540 416 P.BE-SFC-DC-PB-SV
		For CANopen interface	For DeviceNet interface
	DE	540 423 P.BE-SFC-DC-CO-DE	555 879 P.BE-SFC-DC-DN-DE
	EN	540 424 P.BE-SFC-DC-CO-EN	555 880 P.BE-SFC-DC-DN-EN
	ES	540 425 P.BE-SFC-DC-CO-ES	555 881 P.BE-SFC-DC-DN-ES
	FR	540 426 P.BE-SFC-DC-CO-FR	555 882 P.BE-SFC-DC-DN-FR
	IT	540 427 P.BE-SFC-DC-CO-IT	555 883 P.BE-SFC-DC-DN-IT
	SV	540 428 P.BE-SFC-DC-CO-SV	555 884 P.BE-SFC-DC-DN-SV

¹⁾ User documentation in paper form is not included in the scope of delivery

What must be observed when using Festo components?

Specified limit values for technical data and any specific instructions must be adhered to by the user in order to ensure recommended operating conditions.

When pneumatic components are used, the user shall ensure that they are operated using correctly prepared compressed air without aggressive media.

When Festo components are used in safety-oriented applications, the user shall ensure that all applicable

national and local safety laws and regulations, for example the machine directive, together with the relevant references to standards are observed. Unauthorised conversions or modifications to products and systems from Festo involve a safety risk and are thus not permissible.

Festo does not accept any liability for resulting damages.

You should contact Festo's advisors if one of the following apply to your application:

- The ambient conditions and conditions of use or the operating medium differ from the specified technical data.
- The product is to perform a safety function.
- A risk or safety analysis is required.
- You are unsure about the product's suitability for use in the planned application.
- You are unsure about the product's suitability for use in safety-oriented applications.

All technical data applies at the time of going to print.

All texts, representations, illustrations and drawings included in this catalogue are the intellectual property of Festo AG & Co. KG, and are protected by copyright law.

All rights reserved, including translation rights. No part of this publication may be reproduced or transmitted in any form or by any means, electronic, mechanical, photocopying or otherwise, without the prior written permission of Festo AG & Co. KG. All technical data subject to change according to technical update.

Products and services – everything from a single source

Products incorporating new ideas are created when enthusiasm for technology and efficiency come together.

Tailor-made service goes without saying when the customer is the focus of attention.







Pneumatic and electrical drives

- Pneumatic cylinders
- Semi-rotary drives
- Handling modules
- Servopneumatic positioning systems
- Electromechanical drives
- Positioning controllers and controllers

Valves and valve terminals

- Standard valves
- Universal and applicationoptimised valves
- Manually and mechanically actuated valves
- Shut-off, pressure control and flow control valves
- Proportional valves
- Safety valves

Fieldbus systems/ electrical peripherals

- Fieldbus Direct
- Installation system CP/CPI
- Modular electrical terminal CPX

${\bf Compressed~air~preparation}$

- Service unit combinations
- Filter regulators
- Filters
- Pressure regulators
- Lubricators
- On-off and soft-start valves
- Dryers
- Pressure amplifiers
- Accessories for compressed air preparation

Components

Customer-specific solutions

Modules

Industry-specific solutions

Services from Festo to increase your productivity – across the entire value creation sequence



Engineering – for greater speed in the development process

- CAD models
- 14 engineering tools
- Digital catalogue
- FluidDRAW®
- More than 1,000 technical consultants and project engineers worldwide
- Technical hotlines



Supply chain – for greater speed in the procurement process

- E-commerce and online shop
- Online order tracking
- Euro special manufacturing service
- Logistics optimisation



Gripping and vacuum technology

- Vacuum generators
- Vacuum grippers
- Vacuum security valves
- Vacuum accessories
- Standard grippers
- Micro grippers
- Precision grippers
- Heavy-duty grippers



Sensors and monitoring units

- Proximity sensors
- Pressure and flow sensors
- Display and operating units
- Inductive and optical proximity
- sensorsDisplacement encoders for positioning cylinders
- Optical orientation detection and quality inspection



Controllers/bus systems

- Pneumatic and electropneumatic controllers
- Programmable logic controllers
- Fieldbus systems and accessories
- Timers/counters
- Software for visualisation and data acquisition
- Display and operating units




Accessories

- Pipes
- Tubing
- Pipe connectors and fittings
- Electrical connection technology
- Silencers
- Reservoirs
- Air guns

All in all, 100% product and service quality

A customer-oriented range with unlimited flexibility:
Components combine to produce ready-to-install modules and systems. Included in this are special designs – since at Festo, most industry-specific products and customer-specific solutions are based on the 23,000 plus catalogue products. Combined with the services for the entire value creation sequence, the end result is unbeatable economy.



Assembly – for greater speed in the assembly/commissioning process

- Prepack
- Preassembly
- Turnkey pneumatics
- Handling solutions



Operation – for greater speed in the operational process


- Spare parts service
- Energy saving service
- Compressed air consumption analysis
- Compressed air quality analysis
- Customer service

Aspects of quality

Quality can be viewed from a number of aspects. A short virtual tour of the Research and Development department, the Production department or the Customer Service Centre speaks more than a thousand words.

3D engineering and simulation





Innovation quality

Let's look at some of the figures:

- 6.5% of turnover
- 2,800 patents with 100 new applications every year
- 3D engineering and simulation
- 10,600 employees worldwide
- Each and every one of them a lateral thinker

Production quality

Your interest is quality and economy – therefore we place considerable value on:

- Minimum production tolerances
- Ultra-modern, proprietary production methods
- Core competencies in production
- Defined quality standards across the entire production chain
- Strict quality assurance systems: on that you can depend.







Price quality

More service for less money. Many of the new and further developments in the Festo product range have one thing in common: they are technically superior and more attractively priced than their predecessor product. Examples are to be found in all product segments: among the drives, valves, valve terminals; among the service units, and among the range of accessories.

Range quality

For individual solutions. Festo offers components as industry-specific catalogue products as well as standards-based and highly individual special designs. Ready-to-install combinations of these components play an integral part in the Festo product portfolio as modules or systems. Incidentally, an increasing number of components can be individually configured as modular products.

Didactic quality

To complement the products and services for automation, Festo Didactic offers exceptionally efficient training hardware, learning software and seminars of the highest quality. Optimally tailored to your value creation sequence.

In short – training in practical applications for practical application.