



Manometers with measuring membrane

Type:
11MT 63M R
11MT 63M AC
11MT 100M R
11MT 100M AC

Mounting

Radial (R)
Central axial stub (AC)

Usage

For measuring of pressure and vacuum of non - crystallizing gasses, not-aggressive copper and copper alloys.

Nominal dimensions (ND)

63, 100 mm

Class of precision

ND63	- 1,6
ND100	- 1,6

Measurement ranges

kPa	mbar
0 ... 2,5	0 ... 25
0 ... 4	0 ... 40
0 ... 6	0 ... 60
0 ... 10	0 ... 100
0 ... 16	0 ... 160
0 ... 25	0 ... 250
0 ... 40	0 ... 400
0 ... 60	0 ... 600
-2,5 ... 0	-25 ... 0
-4 ... 0	-40 ... 0
-6 ... 0	-60 ... 0
-10 ... 0	-100 ... 0
-16 ... 0	-160 ... 0
-25 ... 0	-250 ... 0
-40 ... 0	-400 ... 0
-60 ... 0	-600 ... 0

Mano - vacuum - meters – the sum from the absolute values of the pressure and vacuum = 2,5; 4; 6; 10; 16; 25; 40 and 60 kPa.

Recommended measuring values

At static loads	- 3/4 from the scale range
At pulsing loads	- 2/3 from the scale range
At a brief measuring	- the scale range

Permitted temperatures

Ambient	$T_{min} - 20^{\circ}\text{C}$	$T_{max} + 60^{\circ}\text{C}$
Of the measured fluid	$T_{max} + 100^{\circ}\text{C}$	

Stub-types

Brass, radial (bottom connection) or central axial (rear connection) with mounting thread and wrench number :

ND63	- M12x1,5 (G 1/4") SW 14
ND100	- M20x1,5 (G 1/2") SW 22

Measuring element

Alloyed copper, measuring membrane

Driving mechanism

Alloyed copper

Corrector of the "O" (zero) position of the arrow

Front view through the dial



Dial

aluminium, white
graduation - black

Arrow

aluminium, black

Box

CrNi steel

Options

FA	- front mounting flange
FB	- rear mounting flange
ST	- mounting clamp (to a panel)
DI	- pin throttle


Other mounting threads

Other measuring units



**Manometers with measuring
membrane**
Mounting and overall dimensions

Type:
11MT 63M R
11MT 63M AC
11MT 100M R
11MT 100M AC



ND	Dimensions [mm]									Weight [kg]	
	a	b	b1	D	D1	h	B	G	SW		
63	8	24	33	63	70	55	57	M12x1,5	G1/4"	14	0,180
100	13	36	46	100	110	80	72	M20x1,5	G1/2"	22	0,460

AUSTA Ltd. reserves the right to change the design and dimensions of the devices without changing the type and way of measurement.